

16- Channel Active Video Hub
Model Number: SJ-S-A16

Product Description:


SJ-S-A16 is 16-channel active receiver Hub. It is suitable for centralized mounting of big project.

Product Feature:



- ◆ Transmission distance of color signal via CAT5 or CAT6
 Up to 800m (2667ft) with passive transmitter Up to 1500m (5000ft) with active transmitter
- ◆ Suitable for direct installation in surveillance cabinets
- ◆ Excellent anti-interference ability
- ◆ Brightness and gain adjustment independently
- ◆ Built-in transient protection, Signal indicator



Product Terminal and Dimension Introduction:




- (1) -- Power INPUT
- (2) -- Video +
- (3) -- Video -
- (4) -- Video INPUT
- (5) -- GND
- (6) -- Video OUTPUT
- (7) -- DIP Switch
- (8) -- Power Switch
- (9) -- Power Indicator
- (10) -- Potentiometer
- (11) -- Signal Indicator



RJ45 Pins ,Product Code Settings:

	200m	400m	600m	800m	1000m	1200m	1500m
1	ON	OFF	OFF	OFF	OFF	OFF	OFF
2	OFF	ON	OFF	OFF	OFF	OFF	OFF
3	OFF	OFF	ON	OFF	OFF	OFF	OFF
4	ON	OFF	OFF	ON	OFF	OFF	OFF
5	OFF	OFF	OFF	OFF	ON	OFF	ON
6	OFF	OFF	OFF	OFF	OFF	ON	ON



Product Installation Instructions:

- ◆ Connect POWER+/- terminal to power, then power indicator becomes light.
- ◆ Select one pair of UTP cable (It must be the same color) and respectively connect to VIDEO +/- of transmitter
- ◆ Connect display device to BNC terminal of transmitter
- ◆ Adjust dip switch for distance in line with above dip switch diagram.

Product Connection Diagram:

